



GH1201

Handheld GPS/GSM Tracker

Homecare.

Children, old people, pets etc. tracking and personal security.

Security.

GeoFence function, emergency calls (E112, E911).

Business.

Employees, cars, goods real-time tracking and protection, command and control from Monitoring Center.

- * Protect your children!
- * Take care of your pets!
- * Search and rescue (SAR)!
- * Protect your rental devices!
- * Manage and secure your fleet and workforce!

ENJOY POCKET-SIZE AND LIGHT-WEIGHT!

Teltonika HandHeld Tracker is a handheld terminal with GSM and GPS connectivity, which is able to get device coordinates and transfer them via GSM network. No installation is required. This device is perfectly suitable for applications where location acquirement of remote objects is needed and perfectly suites for securing company's assets. Small size, long lifetime, mobility and universal configuration of the device ensures wide spectrum of its application: from people tracking, track control to special or secret tasks. GeoFence function allows to set restricted goegraphic areas and device will send warning messages whenever the object crosses the zone (in or out). Device can be used as USB GSM modem. High GPS receiver sensitivity makes device easy to integrate in any environment where ordinary GPS receivers can not fix their position. The whole of the mentioned advantages makes this solution very attractive for companies which success depends on quality of transportation, logistics and movable object monitoring.



What you get:

- * Combination of GPS and GSM wireless networks.
- * Device configuration by SMS or from PC.
- * Secure property via Geofence Protection.
- * Real-Time tracking from the Internet.
- * Device works in Sleep, Logging and Alarm modes.
- * Low Battery notification by SMS.
- * USB GSM Modem function.

Package contents:

- * GH 1201 Handheld Tracker
- * CD with Software
- * USB-Cable
- * Screwdriver
- * Battery
- * Lineyard
- * User Manual
- * 220V Charger

Optional accessories:

- 1. 12V car charger
- 2. Leather holder
- 3. Battery 1750 mAh
- 4. Power Pack

Main features:

	GH1201
GPS Chipset	SiRF Star III 20 channels
GPS antenna	Internal Omni-Directional
GSM	900/1800 MHz and 850/1900 MHz
GPRS	Class 10 data
Voice calls	YES
Vibro	YES
Connectivity	SMS, GPRS
Connection to PC	YES (USB)
NMEA Output	YES (USB)
Configuration	via SMS, GPRS or USB
Internal memory	1MB
Buttons	6
Switches	1 (Keyboard Lock)
Alarm button	YES
Battery	Li-lon (750 mAh)
Battery charging	YES (USB)
LED	3 (Power, GSM, GPS)
Dimensions	91 x 44 x 19 mm
Weight	80 g









GH1201

Handheld GPS/GSM Tracker

TELTONIKA UAB Saltoniskiu str. 10C, LT-08105, Vilnius, Lithuania Phone: +370 5 2127472

Fax: +370 5 2761380 info@teltonika.lt www.teltonika.eu